

**GENERAC**

**HOMELINK** 



**Upgradeable Manual Transfer Switch**

# HOMELINK™

## Pre-Wired 8-10 Circuit Manual Transfer Switch Kit

Generac's HomeLink™ Upgradeable Transfer Switch goes beyond what other manual transfer switches can do. It makes upgrading from a portable generator to automatic standby power simple and affordable.

HomeLink™ is a pre-wired electrical device that's installed next to your home's circuit panel. During an outage, it delivers power to hard-wired appliances (such as furnace, well pump and lights) with the push of a button, safely and easily – eliminating the need for multiple extension cords.



Click switch to generator power or utility power



Plug one end of the cord into the 30 Amp outlet on the generator, and the other end into the power inlet box



## Features

**Safe** – prevents dangerous back-feeding to avoid injuring utility line workers

**Versatile** – can be upgraded later for use with a Generac Home Standby generator (max 11kw)

**Power indicator lights** – displays when you have utility or generator power present

**Powers hard-wired circuits** – directly powers hard-wired appliances such as your furnace, well pump and lights

**Easy to maintain and expand** – interchangeable type circuit breakers make it easy to reconfigure, replace or expand from 8 to 10 circuits in your switch

**Pre-wired** – for quick and easy install



## From Manual to Automatic - Essential Circuit Coverage

You've decided it's time to install an automatic standby generator. You're halfway there. A certified electrician will change out the panel located in the HomeLink™ with an automatic switch upgrade panel and new faceplate – and it's ready to be connected to a home standby generator.

A Generac home standby generator automatically backs up essential circuits with this pre-wired transfer switch. It comes standard with 8 circuits, expandable to 10 circuits.



Protect what's most important to you with

**HOMELINK™**

## HomeLink Manual Transfer Switch Specifications



Model	6852	6853	6854
Max Amps @ 240V	30 Amp	30 Amp	30 Amp
Enclosure	Indoor (NEMA 1)	Indoor (NEMA 1)	Indoor (NEMA 1)
Circuits Provided	8	8	8
Included Breakers	1- 30 Amp 2- pole 1- 20 Amp 1- pole 5- 15 Amp 1- pole	1- 30 Amp 2- pole 1- 20 Amp 1- pole 5- 15 Amp 1- pole	1- 30 Amp 2- pole 1- 20 Amp 1- pole 5- 15 Amp 1- pole
Max Number of Circuits	10	10	10
Accepts Arc-Fault and GFCI Breakers	Yes	Yes	Yes
Prewired	Yes	Yes	Yes
Required Main Breaker in Load Center (provided by installer)	50 Amp 2 pole	50 Amp 2 pole	50 Amp 2 pole
Outdoor Power Inlet Box	NA	30 AMP Resin	30 AMP Aluminum
Kit Contents	<b>Transfer Switch</b> Install manual, wiring harness, conduit and fittings	<b>Transfer Switch</b> <b>Cord:</b> 10' 10/4 with L14--30 ends <b>Power inlet Box:</b> 30Amp resin (must be hardwired) Install manual, wiring harness, conduit and fittings	<b>Transfer Switch</b> <b>Cord:</b> 10' 10/4 with L14--30 ends <b>Power inlet Box:</b> 30Amp aluminum (must be hardwired) Install manual, wiring harness, conduit and fittings
Dimensions (L" x W" x H")	15.4" x 15.8" x 4"	15.4" x 15.8" x 4"	15.4" x 15.8" x 4"
Product Weight (lbs)	26	27.5	27.2
UPC Number	696471068528	696471068535	696471068542
Warranty	5 Year Limited	5 Year Limited	5 Year Limited

## HOME STANDBY GENERATORS

### The Safe, Automatic Solution for Home Backup.

The power goes out and the generator goes on – whether you are home or away. It's that simple. Install the #1 selling home standby generator from Generac and never again deal with extension cords or refuelling in a storm. Instead, enjoy safe, automatic home protection from the inconveniences and potentially dangerous effects of power outages. There's nothing like the peace of mind a Generac automatic home standby generator can give to you and your family.



# AUTOMATIC 24/7 POWER PROTECTION

OL1920 / Printed in USA / Rev. A 01/2015  
©2015 Generac Power Systems, Inc. All rights reserved.  
Specifications are subject to change without notice.

### Portable power since 1959

Since the original portable that started it all in 1959, Generac has continued to engineer advances in standby power for more than fifty years. Generac's product range includes power solutions from portable and automatic home standby generators to backup systems for commercial and industrial applications, all backed by an extensive nationwide service network of certified dealers. Because of our ongoing commitment to quality and innovation, Generac is the name home and business owners have come to trust.

### Portable Parts and Service

Generac portable generators are supported through an extensive nationwide service network that provides parts and technical support to homeowners and contractors. For a portable generator dealer near you, visit [generac.com](http://generac.com).

## GENERAC®

Generac Power Systems, Inc.  
S45 W29290 Hwy. 59  
Waukesha, WI 53189  
1-888-GENERAC (1-888-436-3722)

[generac.com](http://generac.com)