

---

# Residential/Light Commercial Generator Accessories

---

## KOHLER Power Systems

### Fuel Regulator Heater Kit

---

**ISO 9001**  
KOHLER  
POWER SYSTEMS  
NATIONALLY REGISTERED



GM79141-KP1-QS  
20RES/20RESA

### Applicable Models

- 20RES
- 20RESL
- 20RESA
- 20RESAL

### Description

Regulator heater kit GM79141-KP1 is designed for Kohler® 20 kW residential/light commercial generator sets. The regulator heater kit is recommended for reliable engine starting in temperatures from  $-18^{\circ}\text{C}$  to  $-29^{\circ}\text{C}$  ( $0^{\circ}\text{F}$  to  $-20^{\circ}\text{F}$ ). The regulator heater is a 127 mm (5 in.) diameter round heating pad with a snap action thermostat and a power cord. The heating pad mounts directly on the fuel regulator, which is located on the air intake side of the generator set.

The regulator heater requires a source of 120 VAC, 50/60 Hz power. The circuit should be ground fault protected. The generator set is equipped with 120 VAC receptacles for this and other AC-powered generator set accessories. The kit includes an adapter plug for connecting multiple accessories.

## Kit Contents

<b>Models: 20RES/RESL/RESA/RESAL</b>	
<b>Kit: GM79141-KP1-QS</b>	
<b>Description</b>	<b>Qty.</b>
Spacer, steel	2
Adapter, receptacle, 3-wire	1
Heater, regulator pad	1
Screw, hex cap	2
Tie, cable	2
Bushing	1
Installation Instructions	1

## Specifications

<b>Regulator Heater Specifications</b>	
Heater rating	120 VAC, 60 W
Thermostat	4 °C/13 °C (40 °F/55 °F) Snap action
Pad diameter	127 mm (5 in.)
Cord length	610 mm (24 in.)

**DISTRIBUTED BY:**

Availability is subject to change without notice. Kohler Co. reserves the right to change the design or specifications without notice and without any obligation or liability whatsoever. Contact your local Kohler® generator distributor for availability.

© 2013 by Kohler Co. All rights reserved.